

# Digital High/Low Voltage Phasing Meter



- Instrument for measuring overhead and underground voltages (to the nearest 100 volts)
- Two modes of operation AC and Hi-Pot.
- 0-40KV meter up to 240KV with resistors.
- Automatically adjust voltage display to match resistors if used.
- Hi-Pot mode for testing URD Cable.
- In Hi-Pot mode bar graph marks the peak voltage while cable is being charged.
- Large easy to read digital meter and analog bar graph.
- Meter has lighted background that can be turned on for use in poor light conditions.
- Meter enclosure made of high quality rugged extruded aluminum.
- Auto shutdown after 40 minutes if no voltage is detected.
- Long battery life from three AA batteries.
- Auto self test and battery check during start up.
- The coiled, self retracting cable is 16” retracted and 10’ when fully extended.
- Units: Include volt meter, conductor hooks, carry case, batteries, and instructions.

Part Number	Description	Weight (Lbs.)
CPPM-6702	0-40kV Digital Volt Meter w/ conductor hooks. Unit comes complete with carry case battery and instructions.	5.0
CPPM-6703	Pair of Extension Resistors to increase operating range.	1.0